

SMALL BUILDING AUTOMATION CONTROL SYSTEM

BACKGROUND OF THE INVENTION

This application claims priority from U.S. Provisional Application No. 60/261488  
for METHOD, SYSTEM AND APPARATUS FOR SELF-CONFIGURING NETWORK filed  
5 on January 12, 2001 by Arnold et al.

The present invention relates to building control systems, and more particularly to  
control systems for integrating and controlling the operation of various automated applications  
within a small building.

10 In large commercial buildings sophisticated PC networks are used to automate  
and control the operation of HVAC and lighting to assure comfort and efficiency. These  
various Intelligent Building Systems (IBS) may also be configured to monitor the safety of the  
property, contents and people in the building. Whether the building is occupied or empty, these  
IBS systems keep watchful control over the fire and security status, the comfort and energy  
consumption, and the effects of changing weather or occupancy to efficiently operate the entire  
15 physical plant. Specially trained engineers, programmers, commissioning and maintenance  
technicians design, program, install and maintain these expensive and complex multiple IBS  
systems. After installation, the complexity of these IBS systems requires that they be operated  
by trained building technical and security staff. Typically, this staff is dedicated to the use and  
operation of the various IBS.

20 These IBS systems integrate, at a host level on a PC workstation(s), the  
individual computerized control functions of access, security, HVAC, lighting, and fire  
protection in an effort to provide occupant comfort, safety, and convenience, both during and

after working hours. These IBS systems adjust the building's various applications based upon preprogrammed instructions and can provide management reports of abnormal conditions (alarms), property usage and energy consumption, operating trends and maintenance information. In a complex IBS, these systems may turn on lights, adjust the HVAC for comfort, turn security systems to the occupied status, enable elevators, and compensate for prevailing weather at the beginning of a day. At the end of the day these complex IBS's may reverse the process to maximize efficiency, minimize energy cost and provide for occupant and property protection. The interaction of preprogrammed parameters, real time sensor inputs, and operating events make these IBS's adjust automatically to schedules, occupant requirements, and the need of the management for timely indications of, and interactions for, planned and exceptional circumstances.

Unfortunately, this level of computerized control and machine interaction is expensive and currently affordable only in large buildings, for example, buildings of approximately 200,000 square feet and larger. The cost of putting a PC into service alone can mean that these IBSs cannot compete within the cost constraints in small buildings. Putting aside the complexity issues attendant to a PC based IBS, widespread acceptance of these IBS in properties with a \$10,000 control budget is unexpected because the cost of adding a PC and associated software alone adds \$3,000 - 30% cost premium to the traditional controls budget. As a result, the control technology available to smaller buildings has been limited to the kinds of discrete stand-alone HVAC control or lighting control, or security system that is used in residential property. For example, small building typically include little more than a timing device for each HVAC unit, lighting control at each lighting panel, and separate burglar alarm

type security. Each device operates independent of the other controls in the building and each has no central point of reporting or adjustment. This means that every change in use or schedule must typically be entered again and again into each controller by the maintenance personnel. Changes of schedule, or season, or use result in tedious and laborious modification to the various discrete applications. In many cases, operating parameters are selected as a matter of convenience for the maintenance person with little concern for efficiency, cost avoidance, or occupant convenience.

### SUMMARY OF THE INVENTION

The aforementioned problems are overcome by the present invention wherein a control system for use in small buildings is provided with a local control interface that is preprogrammed with profiles of various application controllers types which permit autoconfiguration of the application controllers. The local control interface includes means for obtaining the application controller type from each new application controller. The local control interface uses the controller type as a key to access the pre-stored profile for the specific application controller type. The profile provides the local control interface with all control variable information necessary to configure the application controller on the local control interface.

In a preferred embodiment, the local control interface also includes means for obtaining an application controller profile directly from the application controller at the time of configuration. This mechanism is particularly useful when the profile for a specific application controller is not contained in the pre-stored profile database. For example, the local control interface may acquire profiles directly from application controllers that are freely programmable for custom applications not pre-stored in the local control interface's profile database.

The present invention also provides a method for configuring an application controller. In a preferred embodiment, the application controllers include a service pin that is actuated to initiate the automated configuration process. Upon activation of the service pin, the application controller transmits its processor ID to the local control interface. In response, the local control interface assigns a unique system ID to the device and polls the application controller to determine, among other things, its controller type. Once the controller type is determined, the local control interface retrieves the pre-stored profile for that specific controller type. The profiles include all information regarding the control variables associated with a particular controller type.

In a preferred embodiment, the control interface and various application controllers communication over a conventional communications network with explicit messages using explicit addressing. The control interface is preferably preprogrammed with definitions of the various explicit messages that may be sent or received by the control interface. Similarly, each application controller is preferably preprogrammed with definitions of the various explicit messages that may be sent or received by that application controller.

In a more preferred embodiment, the local control interface includes means for periodically sending ping message to each of the application controllers. Depending on the type of application controller, the ping message may include control variables that affect operation of the application controller. The application controllers include means for updating their control variables in accordance with values presented in the ping message. In addition, the application controllers each include means for sending a response to each ping message. The response confirms that the application controller is still available on the network and, depending on the application controller, may return to the local control interface the value of one or more control

variables that may be forwarded to or otherwise affect operation of other application controllers.

The data structure of the ping message for each controller type is preferably preprogrammed into the local control interface, thereby eliminating the need for user input to define these data structures at the time of configuration.

5           In an even more preferred embodiment, the local control interface is pre-programmed to provide integration between applications of various types. In general, the controller interface is preprogrammed to make appropriate changes to one application controller in view of information received from another application controller. The control interface preferably includes sufficient programming to provide integration between HVAC applications, lighting applications, security alarming and card access applications. Even more preferably, the controller interface will also be preprogrammed to provide integration between public utility demand meter reading applications and asset monitoring applications, for example, applications that work with RF asset tags or bar codes to monitor movement and/or status of various assets, and alarm status from a fire alarm system.

10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
22

PCs. Because the local control interface is preprogrammed with profiles for the various application controllers supported by the system, the control system permits self-configuration of the application controllers. The local control interface also permits grouping of various application controllers, including application controllers of different types. This permits group  
5 toggling of occupancy status and potentially other variables, thereby permitting a certain level of integration between applications of differing types, for example the control of lighting and HVAC applications in response to access events. A further level of integration is provided by the explicit messages sent by the local control interface. These messages transfer the value of control variables between application controllers, including application controllers of different types. The network server interface also permits dial-up or Internet-based control and therefore provides additional flexibility in monitoring and controlling the system.

These and other objects, advantages, and features of the invention will be readily understood and appreciated by reference to the detailed description of the preferred embodiment and the drawings.

#### BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 schematic diagram showing the various components of a control system in accordance with a preferred embodiment of the present invention;

Fig. 2 is a block diagram illustrating the components of the local control interface;

Fig. 3 is a block diagram illustrating the components of the HVAC and lighting

20 application controllers;

Fig. 4 is a block diagram illustrating the components of the access control application controller;

Fig. 5 is a schematic diagram of an ASM-1;

Fig. 6 is a schematic diagram of an LCU-1;

Fig. 7 is a typical thermostat module system diagram;

Fig. 8 is a representation of the data structure for an HVAC control ping;

Fig. 9 is a representation of the data structure for an HVAC response message;

5

Fig. 10 is a representation of the data structure for an ACU control ping;

Fig. 11 is a representation of the data structure for an ACU response message;

Fig. 12 is a representation of the data structure for an ASM control ping;

Fig. 13 is a representation of the data structure for an ASM response message;

Figs. 14A-14B are a flow chart showing the steps of a preferred embodiment of

10 the automated configuration process;

Fig. 15 is a representation of the data structure for an access request message;

Fig. 16 is a representation of the data structure for an access response message;

Fig. 17 is a representation of the data structure for a door user message;

Fig. 18 is a representation of the data structure for an alarm message;

Fig. 19 is a representation of the data structure for an LCU control ping; and

Fig. 20 is a representation of the data structure for an LCU response message.

## DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

### I. Control System Overview

20 A schematic diagram illustrating the architecture of a control system according to a preferred embodiment is shown in Fig. 1 and generally designated 10. The control system 10 is a distributed control system having a local control interface 12 and a plurality of application controllers 14, 15, 16 and 18 interconnected by a conventional communications network 20. The local control interface 12 manages the control system 10 providing direct digital control of the

application controllers. Each application controller controls operation of a corresponding application, such as HVAC application controller 14, card access/security application controller 16, lighting application controller 18 and system-wide sensor controller 15. The application controllers are generally stand-alone controllers operating in accordance with various control variables. The local control interface 12 provides a user interface for monitoring system parameters, changing the value of control variables and managing alarms and events. Through this functionality, the local control interface 12 provides integration between application controllers 14, 15, 16 and 18, including application controllers of different types. The local control interface 12 is preprogrammed with profiles of the various types of application controllers 14, 15, 16 and 18 that are supported by the system 10, including the relevant control variables for each. Additionally, the local control interface 12 may acquire a profile from an application controller at the time of self-configuration, for example, if the application is unknown to the local control interface 12 or a new or customized version of the profile is available. Profiles may also be downloaded through the local control interface 12 or remote access such as the Internet or a dialed or direct connection. These profiles permit self-configuration of the application controllers. This specification describes a preferred embodiment of the present invention, providing sufficient detail for one skilled in the art to practice the claimed invention. Additional detail is contained in U.S. Provisional Application No. 60/261,488 for METHOD, SYSTEM AND APPARATUS FOR SELF-CONFIGURED NETWORK, filed January 12, 2001, which is incorporated herein by reference.

object.



## II. Control System Components

As noted above, the present invention is directed to a small building control system including a local control interface 12 and a variety of application controllers 14, 15, 16 and 18 that communicate over a conventional communications network 20.

### A. Communications Network

The communications network 20 may be any of a variety of conventional hardwire networks, for example, Ethernet or other hardwire networking technologies. The control system 10 is also suited for use with a wide range of wireless networking technologies, such as radio frequency, power line carrier, optical and other similar technologies. Further, the control system 10 may include a combination of networking technologies. For example, as shown in Fig. 1, the system 10 may include a primary network section 20a and a network extension section 20b that are interconnected by communication interfaces 20c and 20d. The present invention may also include capabilities for remote networking. Internet, point-of-sale cash register systems, wide area networks and local area networks can be use for remote control and monitoring of the control system 10. As shown in Fig. 1, the system 10 may include a data, web page server 22 to provide an interface for various remote networking capabilities. These various networking technologies are well known to those skilled in the art and therefore will not be described in detail.

### B. Local control interface

As noted above, the control system 10 is managed by a local control interface 12. The local control interface 12 may be implemented using a wide variety of circuit components and circuit layouts. Accordingly, the local control interface will vary from application to application. For largely cost reasons, the local control interface is preferably embodied in a

dedicated control device having only the necessary hardware components. Alternatively, the local control interface can be embodied in a PC, such as a desktop, palmtop, or laptop. For purposes of disclosure, a preferred implementation of the local control interface 12 will now be described.

5 In general, the local control interface 12 includes a display and touch screen 21, a main processor section 22, a network interface processor section 24, a local serial interface section 26, an LCD interface section 28, a touch screen interface section 30 and a power supply section 32. The local control interface 12 preferably includes a conventional color graphic ¼VGA sized LCD display with an integral analog resistive touch screen for input and output. The display and touch screen provide a graphical user interface ("GUI") for data entry and display. The local control interface 12 can alternatively include other types of touch screens or other conventional input and output devices, such as a keyboard. All user input is performed with the touch screen, primarily by touching buttons or icons on the display. The GUI preferably includes soft-keys which permit the user to navigate through menus as necessary to control and  
10  
15  
20 configure the system 10.

Although the main processor section 22 will vary in design and configuration from application to application, in the described embodiment the main processor section 22 includes an AM186EM 16 bit embedded microprocessor 40; two 2 Mbit FLASH reprogrammable firmware memory chips 42 that contain the program executed by the main  
20 processor; two 1 Mbit MC434000n static RAM chips 44 that provide memory for temporary data storage, database storage and communications buffers; an address decode section utilizing a GAL 16V8 programmable logic device 46 that provides input/output interfacing; a synchronous serial interface (not shown) is embedded within the AM186EM microprocessor to communicate

with touch screen controller 48; a nonvolatile Real Time Clock RTC 50; two software controlled status light emitting diodes 52 for the indication of program status and verification of reception of a network identification message; a clock 54 having a 20.0 Mhz crystal and discrete components that cause the AM186EM microprocessor to operate at the proper frequency. The main processor 22 preferably also includes an ADM691A power-on reset controller 56 to ensure that the power supply is stable and within proper operating tolerances and that the AM186EM microprocessor is initialized properly. The ADM691A controller preferably includes a watch-dog timer to reset the AM186EM microprocessor in the event of a software hang-up. A battery switch-over circuit (not shown) permits the nonvolatile retention of the database in the event of a loss of power. The battery switch-over circuit includes a disabling device, such as an external jumper, that permits the battery back-up to be disabled for clearing the database as desired. The database may also be cleared through an installer menu function in software on the local control interface.

The network interface processor section 24 provides an I/O space mapped interface to the Echelon LonWorks network and offloads certain low-level functions from the AM186EM processor, such as low-level network protocol and driver functions. The network interface processor 24 generally includes an MC143150B1FU1 Neuron processor 58 or its equivalent that executes an Echelon-supplied software program (e.g. Neuron "C" Program); an AT29C010N FLASH reprogrammable firmware memory chip 60 to contain the Echelon-supplied software program; a 43256AGU static RAM chip 62 for temporary data storage and communication buffers; an address decode section 64; a service switch and LED (not shown) are connected to the Neuron processor to indicate the service status condition of the network processor; a power-on reset controller 56 (essentially shared with main processor section 22)

used to ensure that the power supply is stable and within proper operating tolerances; LED indicators 52 (shared with main processor section 22) to indicate the status of network activity and to indicate network processor transmission; and a clock 66 having a 10.0 Mhz. crystal and discrete components causing the Neuron processor 58 to operate at the proper frequency. The network interface processor section 24 also preferably includes an intercontroller network interface section 68 that supplies external network communications from the controller interface to the applications controllers. The network interface processor section 24 preferably includes an FTT10A Free Topology Transceiver (not shown) and its associated circuitry (not shown) and/or, an LT485 EIA485 differential transceiver (not shown) and its associated circuitry (not shown). The specifications of the FTT10A transceiver are described in more detail in "LonWorks FTT-10A Free Topology Transceiver User's Guide," which is published by and available from Echelon Corporation, and is incorporated herein by reference. When the network interface section 24 is used for only FTT10A communication, the FTT10A transceiver (not shown) is connected directly to the Neuron processor (not shown). When the network interface section 24 is used for both FTT10A and EIA485 communication, independently or together, the FTT10A transceiver (not shown) is connected directly to an EIA485 transceiver (not shown) and on to the EIA485 multi-drop network. A one-shot multivibrator (not shown) and inverting Schmidt trigger (not shown) are used to supply a delayed enable signal to the transceiver from the data activity on the FTT10A transceiver. The EIA485 transceiver provides the network connection for the Neuron processor. Alternatively, either the FTT10A and/or the EIA485 on the preferred implementation, or a different interface such as a PLT22 power line transceiver could be used. The actual protocol used is the Echelon LonWorks Manchester-based (for FTT10A or EIA485 interfaces) or the Echelon LonWorks special mode interface (for PLT22 or other power line

interfaces). The Echelon LonWorks protocols are well known to those skilled in microcontroller designs. The technology that allows for simultaneous communication sharing between the FTT10A medium and the EIA485 medium is described in U.S. Patent 6,046,657 to Kikta, which is incorporated herein by reference.

5           The local serial interface section 26 provides an interface between the main processor section 22 and a personal computer or CRT terminal to be used for initialization and database downloading. The local serial interface section 26 preferably includes a MAX202 EIA232 interface transceiver (not shown). The serial port used for communications between the main processor section 22 and the PC is embedded within the AM186 microprocessor.

10           The LCD display interface section 28 utilizes an SED1374 memory mapped LCD controller 70 to drive the color LCD module. This device performs all the data stream formatting, color look-up table translation, and timing signals needed by the display. A GAL16V8 programmable logic device (not shown) provides the color/monochrome and 4/8 bit display data path translation as required by the different types of LCD displays that can be used with the design.

15           The touch screen interface section 30 utilizes an ADS7846E touch screen controller/data converter (not shown) in conjunction with two 74HC00 Quad NAND gates to translate the AM186EM microprocessor embedded synchronous serial interface signals to the signals required by the touch screen controller 48. Translation components are well known to  
20 those skilled in that art and therefore will not be described in detail. Suffice it to say that the AM186EM microprocessor has a 16 bit serial interface with a bi-directional data line and two mutually exclusive selects, but the touch screen controller requires separate data in and data out

lines with a single select. The touch screen interface section 30 also contains transient clamping devices (not shown) and filtering devices (not shown) for the touch screen.

The power supply 32 provides the operating voltages as required by each section of the local control interface 12. The input supply is filtered for EMI and RFI emissions using conventional components (not shown). Overcurrent protection is also provided using conventional components (not shown). For interoperability with certain brands of controllers that use a full-wave-bridge power input structure to rectify a 24 volt AC input, a separate power connection may be provided. The primary supply is an LM2575-5.0 switching step-down converter (not shown) with a fixed output of +5 volts at 1 amp. This supply is used as an input source for all other power supply sections to generate secondary outputs.

The local control interface 12 may also include an Ethernet/phone line interface section 72. This section includes conventional interface circuitry 74, an Ethernet controller 76 with clock 78 and a phone modem 80.

The preceding description of the controller interface 12, including the section configuration and specific circuit components is merely exemplary. The precise configuration of the controller interface 12 will vary from application to application as desired.

### C. Application Controllers

As noted above, the present invention includes a plurality of application controllers 14, 15, 16 and 18 that control operation of corresponding applications, such as HVAC control, access control, system-wide sensors, security and lighting control. The various application controllers are typically capable of operating in stand-alone mode with no intervention from the local control interface 12. Accordingly, each application controller includes generally conventional hardware and software components capable of providing stand-

alone control of the corresponding application. To provide control and system-wide integration, the application controllers are capable of exchanging communications with the local control interface 12. Accordingly, each application controller 14, 15, 16 and 18 includes generally conventional hardware components capable of exchanging messages over the communications  
5 network.

The following paragraphs describe the general function of the various application controllers supported in the preferred embodiment of the present invention. Each of these application controllers is capable of communicating over a LonWorks network.

The various HVAC application controllers, namely the DXU-1, DXU-2, AHU-1, FCU-1, FCU-2, FCU-3, FCU-4 and HPU-1, are similar in circuit design and general layout. Each of these HVAC controllers 14 generally includes sensor inputs 84, control outputs 86, auxiliary input/output points 88 and a zone sensor/display/interface 90.

The DXU-1 is a self-contained controller for a single zone direct exchange ("DX") package, such as a rooftop DX unit. The DXU-1 controls DX units with up to two stages of heating and two stages of cooling. The DXU-1 maintains the temperature of a space to a defined setpoint. The DXU-1 supports individual setpoints for occupied/unoccupied heat and cool. Control is achieved by sequencing the heating and cooling stages based on the current space requirements. The DXU-1 includes digital inputs for fan status, mixed air low limit indication, smoke detector and filter status. A two wire serial interface is provided for the  
10 thermostat and digital outputs in the form of triacs for fan start/stop, two heating stages and two  
15 cooling stages. The DXU-1 energizes the fan when there is a call for heating or cooling, and preferably can be overridden from a local thermostat. Each DXU-1 interfaces to a conventional  
20 local thermostat that provides a space temperature sensor, temperature setpoint adjustment,

occupancy override and a fan auto/on selection. The operating mode of the DXU-1 is normally determined by the local control interface 12. If desired, the DXU-1 may include a local backup schedule to determine operation when the local control interface 12 is unavailable. The DXU-1 monitors the status of the fan. If the fan is energized and no air flow is detected after a

5 predefined period of time, the DXU-1 turns off the fan and all stages of heating and cooling. In addition, an alarm is sent to the local control interface 12. The DXU-1 will return to operation after a reset. The DXU-1 also monitors a digital input for the presence of smoke. If the presence of smoke is detected, the DXU-1 turns off the fan and all stages of heating and cooling. In addition, an alarm is sent to the local control interface 12. The DXU-1 will return to operation after a reset. The DXU-1 further monitors the status of the air filter. An external pressure switch is wired to the input to determine when the filter becomes dirty. The DXU-1 reports an alarm to the local control interface 12 when the filter becomes dirty. The DXU-1 provides mixed air low limit protection. If a low limit condition exists, the DXU-1 turns off the fan and all stages of heating and cooling. In addition, an alarm is sent to the local control interface 12. The DXU-1 will return to operation after a reset. The DXU-1 also monitors the runtime of the cooling stages, heating stages and fan, and reports an alarm to the local control interface when any one of them exceeds its predefined limit. In addition, the DXU-1 preferably reports an alarm to the local control interface when the space temperature drops below a predefined minimum or rises above a predefined maximum. The DXU-1 preferably sends a return to normal alarm when the space

10  
15  
20

temperature returns to the proper range.

The DXU-2 is a self-contained controller for a single zone DX package with an economizer. The DXU-2 controls DX units with up to four stages of cooling, two stages of heating and an economizer. The DXU-2 maintains the temperature of a space to a defined



setpoint. The DXU-2 supports individual setpoints for occupied/unoccupied heat and cool. Control is achieved by controlling the economizer position and by sequencing the heating and cooling stages based on the current space requirements. The DXU-2 includes digital inputs for fan status, mixed air low limit indication, smoke detector and filter status, and analog inputs for mixed air temperature, return air humidity and supply air temperature. A two wire serial interface is provided for the thermostat and digital outputs are provide in the form of triacs for fan start/stop, two heating stages, four cooling stages and a two-position economizer. In addition, the DXU-2 may include an analog output to control a modulated economizer (if desired). With the exception of its ability to control four stages of cooling and an economizer, the operation of the DXU-2 is generally identical to that described above in connection with the DXU-1.

The AHU-1 is a self-contained controller for a single zone air handler ("AHU") with a modulated economizer. The AHU-1 controls AHUs with modulated cooling, modulated heating and a modulated economizer. The AHU-1 maintains the temperature of a space to a defined setpoint. The AHU-1 supports individual setpoints for occupied/unoccupied heat and cool. Control is achieved by modulating the economizer dampers, heating valve and cooling valve based on the current space requirements. The AHU-1 preferably includes digital inputs for fan status, freeze indication, smoke detector and filter status, as well as analog inputs for mixed air temperature, return air humidity and supply air temperature. A two wire serial interface is provided for the thermostat. The AHU-1 also includes analog outputs for the heating valve, cooling valve and economizer. The AHU-1 also includes digital outputs for controlling the unit supply fan (in the form of a triac) and for controlling a two-position economizer (if desired). The AHU-1 energizes the fan when there is a call for heating or cooling, and preferably can be

overridden from a local thermostat. Each AHU-1 interfaces to a conventional local thermostat that provides a space temperature sensor, temperature setpoint adjustment, occupancy override and a fan auto/on selection. The operating mode of the AHU-1 is normally determined by the local control interface 12. If desired, the AHU-1 may include a local backup schedule to  
5 determine operation when the local control interface 12 is unavailable. The AHU-1 monitors the status of the fan. If the fan is energized and no air flow is detected after a predefined period of time, the AHU-1 turns off the fan and closes the heating and cooling valves. In addition, an alarm is sent to the local control interface 12. The AHU-1 will return to operation after a reset. The AHU-1 monitors an input for the presence of smoke. If the presence of smoke is detected,  
10 the AHU-1 turns off the fan and closes the heating and cooling valves. In addition, an alarm is sent to the local control interface 12. The AHU-1 will return to operation after a reset. The AHU-1 further monitors the status of the air filter. An external pressure switch is wired to the input to determine when the filter becomes dirty. The AHU-1 reports an alarm to the local control interface 12 when the filter becomes dirty. The AHU-1 provides mixed air low limit protection. If a low limit condition exists, the AHU-1 turns off the fan and closes the heating and cooling valves. In addition, an alarm is sent to the local control interface 12. The AHU-1 will  
15 return to operation after a reset. The AHU-1 also monitors the runtime of the fan and reports an alarm to the local control interface when the runtime exceeds a predefined limit. In addition, the AHU-1 preferably reports an alarm to the local control interface when the space temperature  
20 drops below a predefined minimum or rises above a predefined maximum. The AHU-1 preferably sends a return to normal alarm when the space temperature returns to the proper range.

The FCU-1 is a self-contained controller for a two-pipe fan coil unit ("FCU") with a single coil for heating and cooling. The FCU-1 is designed to control commercial unitary HVAC equipment, and more specifically, FCUs with a single modulated valve and fan. The FCU-1 maintains the temperature of a space at a defined setpoint. The FCU supports individual setpoints for occupied/unoccupied heat and cool. Control is achieved by modulating the cooling/heating valve of a single coil two-pipe fan coil unit based on the current space requirements. The FCU-1 can control heating only, cooling only or heating/cooling fan coil units. Automatic seasonal changeover can be provided by a remote pipe mounted temperature sensor that is placed on the supply water line. The control is switched when the sensor detects a change in supply temperature between hot and cold water. The FCU-1 includes a digital input to monitor equipment status, a two wire serial interface for a thermostat, an analog output for the valve and a triac output for the unit supply fan. Each FCU-1 interfaces to a conventional local thermostat that provides a space temperature sensor, temperature setpoint adjustment, occupancy override and a fan auto/on selection. The operating mode of the FCU-1 is normally determined by the local control interface 12. If desired, the FCU-1 may include a local backup schedule to determine operation when the local control interface 12 is unavailable. The FCU-1 monitors the status of equipment within the unit. An external contact may be wired to the input to provide additional equipment safety interlocks. When the contact closes, the FCU-1 shuts the unit down and an alarm is reported to the local control interface. The FCU-1 also monitors the runtime of the fan and reports an alarm to the local control interface when the runtime exceeds a predefined limit. In addition, the FCU-1 preferably reports an alarm to the local control interface when the space temperature drops below a predefined minimum or rises above a predefined maximum.

The FCU-1 preferably sends a return to normal alarm when the space temperature returns to the proper range.

The FCU-2 is a self-contained controller for a two-pipe FCU with a single coil for heating and cooling. The FCU-2 is designed to control FCUs with a single floating setpoint valve and fan. The FCU-2 includes a digital input to monitor equipment status, a two wire serial interface for a thermostat, a floating setpoint output for the valve and a triac output for the unit supply fan. The FCU-2 is generally identical in configuration and operation to the FCU-1, except that it is adapted to control a floating setpoint valve. Accordingly, the FCU-2 will not be described in further detail, reference instead being made to the above description of the configuration and operation of the FCU-1.

The FCU-3 is a self-contained controller for a four-pipe FCU with a single coil for heating and cooling. The FCU-3 is designed to control FCUs with dual modulated valves and a fan. The FCU-3 maintains the temperature of a space at a defined setpoint. The FCU supports individual setpoints for occupied/unoccupied heat and cool. Control is achieved by modulating the cooling and heating valves of a dual coil four-pipe fan coil unit based on the current space requirements. The FCU-3 includes a digital input to monitor equipment status, a two wire serial interface for a thermostat, two analog outputs to control the valves and a triac output for the unit supply fan. Like the FCU-2, the FCU-3 is generally identical in configuration and operation to the FCU-1, except that it is adapted to control dual coil four-pipe fan coil unit. Accordingly, the FCU-3 will not be described in further detail, reference instead being made to the above description of the configuration and operation of the FCU-1.

The FCU-4 is a self-contained controller for a four-pipe FCU with a single coil for heating and cooling. The FCU-4 is designed to control FCUs with dual floating setpoint

valves and a fan. The FCU-4 includes a digital input to monitor equipment status, a two wire serial interface for a thermostat, two floating setpoint outputs for the valves and a triac output for the unit supply fan. The FCU-4 is generally identical in configuration and operation to the FCU-1, except that it is adapted to control two modulated floating setpoint valves. Accordingly,  
5 reference is made to the above description of the configuration and operation of the FCU-1.

The HPU-1 is self-contained controller for liquid source heat pumps. The HPU-1 is designed to control heat pump units with two-stage compressor, reversing valve and fan. The HPU-1 supports individual setpoints for occupied/unoccupied heat and cool. Control is achieved by sequencing the reversing valve and compressor stages of a liquid source heat pump in a conventional manner based on the current space requirements. The HPU-1 include a digital  
10 input for monitoring equipment status, a two wire serial interface for the thermostat and digital outputs in the form of triacs for fan start/stop, two compressor stages and a reversing valve. The HPU-1 maintains the temperature of a space to a defined setpoint. The HPU-1 energizes the fan when there is a call for heating or cooling, and preferably can be overridden from a local  
15 thermostat. Each HPU-1 interfaces to a conventional local thermostat that provides a space temperature sensor, temperature setpoint adjustment, occupancy override and a fan auto/on selection. The HPU-1 preferably monitors the runtime of the fan and reports an alarm to the local control interface when the runtime exceeds a predefined limit. In addition, the HPU-1 preferably reports an alarm to the local control interface when the space temperature drops below  
20 a predefined minimum or rises above a predefined maximum. The HPU-1 preferably sends a return to normal alarm when the space temperature returns to the proper range. The operating mode of the HPU-1 is normally determined by the local control interface 12. If desire, the HPU-

1 may include a local backup schedule to determine operation when the local control interface 12 is unavailable.

The ASM-1 is an auxiliary sensor module that monitors auxiliary sensors. Like other controllers, the ASM-1 controller is based on LonWorks networking technology. In the preferred embodiment, the ASM-1 is a stand-alone microprocessor based controller having analog inputs for outdoor air temperature 190, outdoor air humidity 192 and/or supply water temperature 194 (See Fig. 5). The values determined by these sensors are provided by the ASM-1 to the local control interface 12 for propagation to other application controllers. The ASM-1 may also include demand meter 196, air quality 198 and other desirable inputs, as well as one or more auxiliary outputs 188.

The ACU-1 is a self-contained controller for controlling and monitoring a single controlled access entryway, for example, to control access to various areas of a facility. The ACU-1 is capable of interfacing with one or two card readers 98 and/or keypads, an electronic door strike and a door monitor contact. The ACU may also interface with a conventional asset tag reader to allow the control system 10 to monitor the movement of tagged assets. Each ACU-1 monitors and controls access to a single entry barrier through the use of an entrance card reader/keypad and an optional exit card reader/keypad. The ACU application controller preferably includes supervised inputs that provide for tamper detection. One input is preferably dedicated to monitoring door status, and another is dedicated to monitoring an exit request pushbutton. Two non-dedicated supervised inputs can be used for monitoring other tamper devices, such as a glass break detector or a motion sensor. The ACU application controller also includes digital outputs that control card reader indicators, such as LEDs and audible sounders. The ACU application controller provides 5 VDC outputs to power the card readers. A separate

power supply may be used if a different voltage is required. A relay output is provided to control a barrier locking device, such as a door strike or magnetic lock. Preferably, both normally open and normally closed contract are provided to accommodate barrier locking devices that lock when power is applied or devices that lock when power is off. Alarms are generated when the controller detects that a door has been propped or when a door has been forced open. Alarms are also generated if the two spare supervised inputs have been tampered with.

The LCU-1 is a self-contained controller for lighting controls. The LCU-1 is capable of controlling commercial lighting circuits. Typical applications include interior lighting, parking lot lights and signage. In the preferred embodiment, each LCU-1 is capable of controlling eight individual lighting circuits based on the occupancy status of the zone. Control is providing by switching individual lighting relays (or contactors 92) for each circuit. Each circuit preferably includes an override switch 94 that changes the occupancy status of the zone to "occupied" for a predefined period of time (See Fig. 6). The LCU-1 occupancy status is preferably determined by the local control interface 12. If desired, a backup schedule may be provided on the LCU-1 to permit operation when communications with the local control interface 12 have failed. The LCU-1 may also interface with a photo cell 96 in a conventional manner.

The application controllers may be implemented using a wide variety of circuit components and circuit layouts. Accordingly, the application controllers may vary from application to application. In the preferred embodiment, all HVAC and lighting application controllers are realized on a common platform, while the ACU application controllers are realized on a different platform. For purposes of disclosure, a preferred implementations of the HVAC/lighting application controller and a preferred implementation of the access control

application controller will be described. The various application controllers may be realized on a single printed circuit board design by varying the component population as required.

In general, the HVAC/lighting application controllers each include a processor section 100, an analog/digital input section 102, a digital output section 104, an analog output section 106, a room sensor/thermostat interface section 108, an intercontroller network interface section 110 and a power supply section 112. The processor section 100 preferably includes an MC143150B1FU1 (or equivalent) Neuron Processor 114 which executes a downloadable Neuron "C" program that contains the operating system, communications routines, data constants, hardware I/O drivers, and the application program unique to each controller type. The processor section 100 also includes a NeuroWire 3-wire serial synchronously-clocked simultaneous input/output interface comprised of IO8 Serial Clock [SCK], IO9 Serial Data Output [SDO], and IO10 Serial Data Input [SDI]. The protocol used in this interface is the same as the Motorola Semiconductor SPI or the National Semiconductor Microwire protocols and the actual operation of such is well known to those skilled in microcontroller-based designs. Each device controlled by this interface uses IO8 [SCK] and IO9 [SDO] and/or IO10 [SDI] as required by each device and a processor I/O pin used as a chip select. The processor section 100 further includes an AT29C010N FLASH reprogrammable firmware memory chip 116 used to contain the Neuron "C" program for the given application controller; a 43256AGU Static RAM chip 118 used for temporary data storage and communication buffers; an address decode section 120 utilizing a 74HCT14 hex inverting Schmidt trigger (not shown) and a 74AC32 quad OR gate (not shown); a service switch 122 and LED 124 are connected to the Neuron processor to invoke and/or indicate the service state



condition of the Neuron processor; a DS1811 power-on reset controller 126 used to ensure that the +5 volt power supply is stable and within proper operating tolerances and that the Neuron processor is initialized properly; a clock 128 having a 10.0 Mhz. crystal and discrete components causing the Neuron processor to operate at the proper frequency.

5           The analog/digital input section 102 generally includes a LM358 sensor bias supply Op Amp (not shown) used to supply a precise bias reference to sensors that require bias such as a contact closure, or a thermistor that is used as one leg in a voltage divider with readings subsequently normalized by a program look-up table; an input bias and filter circuit for each of seven input channels (UI1 – UI3 and DI1 – DI4) (For example, channel UI1 is comprised of a 10.0K ohm 1% series resistor and a 0.1 uF capacitor for filtering and transient dissipation. Also there is an optional 10.0K ohm 1% contact closure/thermistor bias resistor and an optional 10.0K ohm 1% input divider resistor populated as required by the particular controller types application program sensor needs); an LM4040-5 precision voltage reference (not shown); a TLC1542 or equivalent successive approximation Analog to Digital converter used to convert the inputs to digital values; a TCF6000D (not shown) and BAV99 (not shown) input transient clamp device used to limit the voltages of the input signals presented to the Analog to Digital converter (not shown); and a comparator (not shown) used to generate a chip select signal to the Analog to Digital converter (when used) when the processor asserts the [IO7] signal above 3.3 volts. To operate the analog input section, the processor and application program communicate with the

10  
11  
12  
13  
14  
15  
16  
17  
18  
19  
20

AD converter via the NeuroWire synchronous full-duplex peripheral interface comprised of a serial clock (SCK)[IO8], serial data out (SDO)[IO9], and serial data in (SDI)[IO10], and a chip select [IO7]. Suffice it to say that the processor clocks a command in to the converter for a particular channel to be converted while simultaneously clocking out the previous conversion

value. The digital input circuitry includes four voltage comparators with hysteresis connected to four discrete I/O lines to the processor. Each circuit has a negative-going input threshold of 1.67 volts and a positive-going threshold of 3.00 volts thereby providing 1.33 volts of hysteresis to prevent false triggering. The output is then coupled to a respective processor I/O line allowing the measurement of digital inputs without the cost or timing constraints of an AD converter for some applications. Both the AD converter and some or all of the digital input comparators may be used in some applications.

The digital output section 104 includes an 8 channel TPIC6x595 NeuroWire-based serial input parallel output open-collector driver (not shown) used to interface to up to eight triac output circuits or up to six BCX70 NPN transistors for direct coupling processor I/O lines to individual triac output circuits. Note that only one or the other approach can be used at one time. The digital output section also includes up to eight triac output circuits each comprised of (output [TO1] for example) an MOC3012 optotriac coupler (not shown), a 2.21K ohm coupler LED current limiting resistor, a triac drive and snubber circuit (not shown), a 2N6073B 400 volt 4 amp triac (not shown), and a metal oxide varistor (not shown)..

The analog output section 106 provides three analog outputs, namely [AO1, AO2 and AO3]. For [AO1], the analog output section includes an LM359 Op Amp based 2 pole low pass filter (not shown) with a gain of 2 that converts a high frequency pulse-width modulated 5 volt digital waveform to a 10 volt DC voltage output. For [AO2] and [AO3], the analog output section includes a TLV5625 dual serial input voltage output digital to analog converter (not shown) coupled with an LM358 dual Op Amp (not shown) each configured for a gain of 3 to effect two additional 10 volt DC voltage outputs. This converter is interfaced via the synchronous serial interface. The design supports DA converters of 8/10/12 bits of resolution.

The room sensor/thermostat network interface section 108 supplies operating power as well as communication to the sensor and generally includes an LM317 adjustable voltage regulator (not shown) configured as a 38 milliamp constant current source; an LM339 voltage comparator and associated discrete circuitry used to receive messages from the thermostat network and relay them to the Neuron processor; a dual BCX70 NPN transistor circuit used to sink the current source to ground to effect transmission of data to the room sensors as modulated by processor I/O line(s) [IO2] and/or [IO9] as required by interface type. The room sensor communicates back to the controller by sinking current in the same manner as the controller. Note that most of the time (even during communication) the network interface is supplying the constant current to the thermostat reservoir capacitor thereby ensuring that the thermostat has adequate operating power. The current protocol used is the proprietary Barber-Colman S-Link (Mu-Link) Sensor Protocol as defined in their confidential internal documentation. Suffice it to say that this is a half-duplex communication interface over a mutually sensed and modulated DC current-limited power line, the mechanics of which have been practiced for many years and the actual operation of such is well known to those skilled in microcontroller-based designs. An alternative that has also been developed uses the same type of mutual sensing and modulation in conjunction with a controller generated Manchester self-clocking (data with inferred clocking via bit cell transition polarity based on the previous data bit) command data stream with a trailing alternating clock/data bit stream for responses. This allows the sensor to be implemented with a very low cost microcontroller that derives all of its communication timing from the controller itself.

The intercontroller network interface section 110 supplies external network communications to the application controller and generally includes an FTT10A Free Topology

Transceiver (not shown) and its associated circuitry or an LT485 EIA485 differential transceiver (not shown) and its associated circuitry, as desired. Alternatively, the intercontroller network interface may include a different interface such as the PLT22 power line transceiver. The actual protocol used is the Echelon LonWorks Manchester-based (for FTT10A or EIA485 interfaces) or the Echelon LonWorks special mode interface (for PLT22 or other power line interfaces). The Echelon LonWorks protocols are well known to those skilled in microcontroller designs. The intercontroller network interface also includes a dual LED (not shown) for indication of the status of network activity via an LM339 comparator and controller transmission.

The power supply section 112 supplies internal operating voltages to the application controller and generally includes a half-wave input rectifier diode (not shown), a current limiting resistor (not shown) and input over current protection (not shown); and a +15 volt supply using an LM317 adjustable linear voltage regulator (not shown), with its output set by appropriate resistors. The voltage regulator does not use a bulk input capacitor, but instead allows its output to "droop" between power line half-wave cycles. This substantially reduces the internal heat generated. The power supply further includes a +5 volt supply using an LM78M05 +5 volt linear voltage regulator (not shown); a comparator and DA converter reference circuit generating both 1.67 volt and 3.3 volt bias.

The ACU application controllers use a somewhat different circuit design than the previously described HVAC and lighting application controllers. The ACU is intended to be used in a distributed networked system with specific peripherals and communication medium. As such, the choices for supplied power and networking technology are made as part of the overall system design and may require external modules to implement. Each ACU application controller generally includes central processing section 150, card reader interface circuitry 152,

sensor loop interface circuitry 154, relay and digital output interface circuitry 156, intercontroller network interface circuitry 158 and power supply section 160.

The central processing section 150 includes an Echelon 3150 Neuron CPU 162 that provides the applications program, I/O point control, and interface to the Lonworks network via either the FTT10A Free Topology Transceiver or an EIA485 Transceiver, as described in more detail below. The Neuron processor 162 includes an EEPROM 167. The central processing section 150 also includes a 32K Byte Static RAM chip 166, and a GAL logic device 168 for address decoding an external EPROM 164, preferably in the form of a 27C010 Flash ROM chip, for the storage of the operating software as well as the application program.

The RAM chip 166 is used to provide additional file buffers for the ACU. The GAL logic device 168 provides the OE\*, the WE\*, the Flash select, and the RAM select, and also generates the output port latch clock. The central processing section 150 also includes a service pin circuit (not shown). The service pin circuit has two functions: first it is driven by a push button autoconfiguration switch 170 to indicate to the Neuron processor 162 that it is required to request service information as described in the Echelon Documentation, second it drives the service LED 172 in conjunction with a 270 ohm resistor. This initiates the self-configuration of the ACU with the LCI, as described in more detail below. The central processing section 150 further includes a system clock oscillator circuit 174 which generate the system clock used by the Neuron processor 162, preferably at 10 MHz; a reset circuit 176 having a DS1233 low voltage reset controller (not shown), 2 4.99K pull up resistors (not shown) and a .001uF timing capacitor (not shown) that is used to monitor the +5V power supply for proper levels; and a real time clock 178.

The Neuron processor 162 uses a Motorola 68HC05P6A I/O microcontroller 180 for the direct interface to the card readers, keypads, and the supervised and unsupervised inputs (not shown). The ACU uses the larger address space of the Neuron processor 162 in order to have greater flexibility in the number of bindings and file buffers available. The I/O microcontroller 180 is connected to a system clock oscillator circuit 180 which generates the system clock used by the I/O microcontroller 180, preferably at 4 MHz. The Neuron processor 162 interfaces to the I/O microcontroller 180 via a seven-bit interface. The Neuron processor 162 queries the I/O microcontroller 180 for messages via the DATA\_RDY and uses the DATA\_SEL0, DATA\_SEL1, and DATA\_TYPE to establish what kind of data and then uses the Neurowire (or SPI) port I/O object to send/receive data to/from the I/O microcontroller 180.

The I/O microcontroller 180 buffers input data from the card reader(s) and/or keypad(s), as well as providing analog and binary inputs. More specifically, supervised input channels are realized via an integral 8 bit 0 to +5 volt analog to digital converter (not shown). The interpretation of an input value is a function of the specific designed use of that input used as a multi-state supervised input. Essentially, a voltage divider made up of the 4.7K ohm loop bias resistors and the end of line resistor installed in each detector is used to determine the state of the loop. The nominal end of line resistor value is 4.7K ohm 5%. The nominal state of the loop with 4.7K ohm is the Normal state. When the end of line resistor changes to 9.4K ohms, a contact open Alarm is reported. When the end of line resistor changes to 2.4K ohms, a contact closed Alarm is reported. When the end of line resistor changes to a short or an open, then a Fault is reported. A transient protector (not shown), plurality of 10K ohm series

resistors, and filter capacitors (not shown) are used to limit and filter the supervised inputs.

The I/O microcontroller 180 also provides unsupervised inputs that are designed to detect binary contact closures to local common. They are realized via the same type input limiting and filtering circuitry as the supervised inputs. In this instance, the input values are read as

5 digital inputs. The I/O microcontroller 180 further includes card reader track data inputs. The card readers' "0" and "1" inputs (Entry reader is used as an example) are connected to pull up resistors (not shown) and to the transient protectors (not shown) and filter capacitors (not shown). They then go to an inverting Schmidt trigger input device (not shown) and a reader type logic selection GAL (not shown) which is connected to two input port pins on the I/O microcontroller 180. In addition, the reader type logic selection GAL (not shown) is connected to the I/O microcontroller's interrupt line. If the Wiegand mode is selected, both data input lines go to the interrupt. If the magnetic mode is selected only the clock (or "0") line is connected to the interrupt. The reader modes are selected by a DIP switch (not shown). When the I/O microcontroller 180 receives these interrupts in conjunction with either of the two input port pins, it buffers the track data from the reader. The second or exit card reader is interfaced in the same manner. The reset controller 176 of the Neuron processor 162 is to connected to a pull up resistor (not shown) and to the I/O microcontroller's reset line via a diode (not shown) to synchronize the reset of the I/O microcontroller 180. In addition, the Neuron processor 162 can directly reset the I/O microcontroller 180 alone via the IO1 line.

20 The ACU includes card reader interface circuitry 152 for interfacing the card reader(s) and/or keypad(s) (not shown) to the I/O microcontroller 180. This circuitry 152 is generally conventional and will therefore not be described in detail.

Similarly, the ACU includes sensor loop interface circuitry 154 for interfacing any external sensors (not shown) to the I/O microcontroller 180. This circuitry 154 is generally conventional and will not be described in detail.


The intercontroller network interface circuitry 158 supplies external network communications. The network interface circuitry 158 generally includes an FTT10A Free Topology Transceiver (not shown) and its associated circuitry or an LT485 EIA485 differential transceiver (not shown) and its associated circuitry, as desired. Alternatively, the intercontroller network interface circuitry 158 may include a different interface such as the PLT22 power line transceiver. The actual protocol used is the Echelon LonWorks Manchester-based (for FTT10A or EIA485 interfaces) or the Echelon LonWorks special mode interface (for PLT22 or other power line interfaces). The Echelon LonWorks protocols are well known to those skilled in microcontroller designs. The intercontroller network interface circuitry 158 also includes a dual LED (not shown) for indication of the status of network activity via an HC86 logic gate and controller transmission.

The relay and digital output interface circuitry 156 provides an output interface for controlling external devices, such as an electronic door strike. More specifically, the ACU has eight digital output bits generated via an AC574 latch (not shown). Seven of these eight lines go an MC1413D relay driver device (not shown). One of these seven drives the strike relay (not shown) for the door strike output. The other six supply open collector sinking digital outputs. The eighth line is connected to the base of a transistor (not shown) which drives a high frequency audio indicator (not shown) or a second relay (not shown) which can be used for a second door strike. The latch (not shown) is memory mapped within the Neuron address



space and the generation of the rising edge write strobe takes place within the GAL logic device 168 based on the address location, R/W, and E. The open collector outputs of the relay device driver are used to sink up to 50 ma loads. The six open collector outputs are transient protected and generally are used for indicators.

5                    The power supply section 160 is a step down (buck) switchmode converter circuit including an input section containing a series diode and an input filter capacitor. This section provides a half wave rectified, filtered DC bus at approximately the peak of the input voltage. An LM2575M-5.0 converter (not shown) provides an output of +5.0 V via an energy storage inductor (not shown), a commutating diode (not shown), and a filter capacitor (not shown). Most of the pins on the converter are connected to the groundplane for heatsinking purposes. A transient protector (not shown) provides transient protection because the +5V can be used to power the readers. The power supply section 160 includes supply selection jumpers (not shown) that are used for the reader power selection. Regardless of the supply selected, there are transient protectors (not shown) and series limiters (not shown) for ACU supply protection.



Many applications will include one or more integrated sensors that provide information to the application controller. These sensors are typically packaged with and often dedicated to use with the specific application. For example, a DX package unit may include an inside temperature sensor that provides inside temperature to the application controller.

20                    In the preferred embodiment, the control system 10 may also includes various network-wide sensors that provide information to the control system 10, which shares that information with those application controllers that use such information. For example, the control system 10 preferably includes an auxiliary sensor module (ASM-1) (described above)

that is a LonWorks communications device which provides input information common to many HVAC control devices, such as outside air temperature, outside air humidity and supply hot water temperature. The local control interface 12 provides the sensed values to the appropriate application controllers over the network. By providing this information universally on the network, the need for separate sensors and individual analog inputs on each HVAC application controller is eliminated.

The control system 10 also preferably includes a thermostat module (DTM-1) for interfacing thermostatic functions to HVAC equipment. The thermostat is a self-contained intelligent thermostat capable of communicating with various HVAC devices over the LonWorks network. A typical thermostat module system diagram is shown in Fig. 7. The thermostat application includes space temperature, setpoint adjust, fan override and occupancy override. In operation, the thermostat permits adjustment of the space temperature setpoint within predefined limits. The thermostat also preferably includes a push-button override that temporarily changes the occupancy status to "occupied."

The control system 10 may include various other sensor modules that provide information that is provided to a single application controller or that is shared with a plurality of application controllers across the network.

### III. Control System Operation

As noted above, the control system 10 is essentially a distributed system with stand-alone application controllers 14, 15, 16 and 18 capable of operating in the absence of communication with the local control interface 12. The local control interface 12 has the ability, among other things, to monitor and adjust control variables in the various application controllers, thereby affecting operation of the various applications. The control system 10 includes various

software components that control operation of the local control interface and application controllers. The design and configuration of these software components will be well within the abilities of one skilled in the art after review of the operation of these components described herein. Accordingly, the software components will not be described in detail.

5

#### A. Operation Overview

The local control interface 12 and application controllers are capable of communicating over a variety of hardwire and/or wireless communication backbones. In the preferred embodiment, the present invention uses Echelon Corporation's LonWorks technology as its communications medium. The network architecture is primarily master/slave with peer-to-

\*

master  
slave.

peer (i.e., application controller to application controller) communications only as required by some applications. The local control interface 12 initiates most exchanges of communication with the application controllers. All communication exchanges are initiated using LonWorks explicit messages with explicit addressing (i.e. direct 48-bit Neuron ID addressing). The local control interface 12 uses Standard Network Variable Types (SNVTs) for the standard data object model values sent via explicit addressing to each application controller. The application controllers 14, 15, 16 and 18 and the controller interface 12 also provide LonWorks SNVTs for access to system features via third-party LonWorks devices. In operation, the local controller interface 12 does not directly manipulate the third-party device's SNVTs using LonWorks Network Management commands, however, third party networking tools can. Although the present invention preferably operates using LonWorks, the control system is well-suited for use with essentially any private protocols or "plug and play" open communications protocols.

\*

The local control interface 12 preferably includes two modes of operation, namely installer mode and user mode. Installer mode permits the user to access and control all aspects of

the local control interface. User mode permits access to only a limited set of commands, thereby reducing the likelihood of accidental or mischievous modification of important system settings.

The precise amount of control permitted in user mode can vary from application to application, but in the preferred embodiment, user mode only permits access to and modification of temperature setpoints for controllers, existing schedules and view/acknowledge alarms.

In the preferred embodiment, the local control interface 12 has the ability to divide the network of application controllers 14, 15, 16 and 18 into occupancy groups. The occupancy groups are used to permit collective control of the member application controllers in each group. For example, the lighting and HVAC applications in a given area can be grouped together into a single occupancy group so that those applications can be operated as a group. The local control interface 12 of the preferred embodiment supports 16 occupancy groups. Each occupancy group includes a schedule and a list of up to 62 application controllers. The occupancy status of an occupancy group can be controlled by the corresponding schedule, via an access controller (such as an ACU-1 as described below) or manually using the local control interface 12.

The local control interface 12 preferably supports up to 16 schedules, one for each occupancy group. The schedules may be used for group occupancy control, timed operation of access control, door mode control, door free access control and lighting control. Each schedule preferably supports up to two start/stop time intervals for each day of the week and up to two start/stop intervals for holidays. The local control interface 12 maintains a database of up to 50 holidays. Holidays can be preprogrammed or user defined after installation.

The local control interface 12 also provides control configuration wizards that walk the user through the steps required to monitor and/or set the control variables for a

particular application controller. The wizards include easy-to-use graphical setup screens for common configuration items, such as occupied/unoccupied temperature setpoints and backup scheduling and alarm limits.

As noted above, the application controllers 14, 15, 16 and 18 operate in accordance with various control variables that are specified by the user (or through pre-set default values). For example, an HVAC application will include a temperature variable that sets the desired inside temperature for the corresponding area. As in many conventional control systems, the application controllers are capable of operating in two distinct modes, one when the area is occupied and one when it is not. For example, an HVAC application may include a first temperature setting to be satisfied when the area is occupied and a second temperature when the area is not occupied.

Although the application controllers are typically capable of operating in a stand-alone mode, they are capable of communicating with the local control interface 12. Through these communications, the local control interface 12 has the ability to set control variables values within the application controllers using explicit messages and SNVTs for data structures. This permits the local control interface 12 to affect operation of the various system applications. The application controllers are preprogrammed with the data structure or format of all explicit messages associated with the controller type. This permits the application controllers to parse and understand the explicit messages. Alternatively, the applications may be downloaded with this information as necessary, for example, to add new explicit messages or to modify existing explicit messages.

In addition to receiving explicit messages from the local control interface 12, most of the application controllers are capable of sending text-based alarms to the local control interface 12 to indicate extraordinary conditions.

In the described embodiment, the local control interface 12 can support from 1 to 5 62 application controllers. The local control interface 12 allows modification of inputs and setpoints for each application controller as well as display of outputs for each controller. The Database:

local control interface 12 maintains a controller database with certain information concerning each application controller. When application controllers are added to the controller database, they are given a default name (i.e. Unit 1 AHU2) which can be modified by the user to any 20-character string. The controller's name is used when assigning it to occupancy groups and for alarm display. Each element in the controller database preferably includes the following attributes:

Name – 18 character ASCII description (user programmable)

Neuron ID – LonWorks 48-bit Neuron ID for device

Program ID – LonWorks Program ID for device (used as device type)

Version ID – ASCII representation of controller's software version

Controller database records for ACU controllers preferably have the following additional attributes:

Exit Group – Group whose occupancy count will be incremented when access attempt successful through exit side of ACU. Entry Group's count will be decremented.

Entry Group - Group whose occupancy count will be incremented when access attempt successful through entry side of ACU. Exit Group's count will be decremented.

Free Access Schedule – specifies a Schedule for controlling ACU's free access status.

ACU will be in Free Access when Schedule is active

Access Mode Schedule – specifies a Schedule for controlling ACU's access mode

Access Mode when Schedule active – mode (card, card+PIN or cipher) for ACU when

Access Mode Schedule is active

Access Mode when Schedule inactive – mode (card, card+PIN or cipher) for ACU when

Access Mode Schedule is inactive

Manual Free Access – forces Free Access active/inactive for ACU

Auto Add on/off – places ACU in to/out of Automatic Card Addition mode

Manual Access Mode – forces ACU into card, card+PIN or cipher access mode

#### B. Preprogramming of Local Control Interface

As described in some detail above, the local control interface 12 allows users to specify occupancy groups, schedules, holidays and setpoints for the various application controllers. This information may be entered into the local control interface 12 using its touch screen. If desired, this information can be entered into a PC-based program and downloaded into the local control interface 12 via the serial port in the AM186EM main processor.

The control system 10 of the present invention permits self-configuration and integrated operation of application controllers of various types. This is preferably achieved by preprogramming the control system 10 with a configuration table that stores profiles for the various controller types recognized by the system 10. Although the precise information included in these profiles will vary for each application controller, these profiles generally include information about the input SNVTs, output SNVTs and configuration SNVTs of all supported controller types. The table and its associated routines provide for lookup of SNVTs by name.

Profile

Input  
table

controller type and controller version ID. The LCI maintains another table of supported data types which provides range, base data type, engineering units, enumerations (if applicable), sub-data types (for structured elements), step for increment/decrement and display routines for each data type. All data types used by the LCI have entries in this table. These tables provide the

- 5 local control interface 10 with sufficient awareness of the application controller to monitor and affect its operation.

In a preferred embodiment, each profile includes a record for each variable supported by the application controller. The record includes a field for variable type, variable name, display name and variable number. The variables are preferably classified in one of three different types--namely, input variables, output variables and input configuration variables. Input variables represent variables that can be sent to the application controller by the local control interface. Output variables represent variables that can sent by the application controller to the local control interface. And finally, input configuration variables are control variables that relate to operation of the application controller, but that are not routinely varied through local control interface 12 commands or otherwise. Each application controller is preferably pre-loaded with default values for all control variables. This facilitates automated configuration, by eliminating the need to provide these control variables with initial values. By way of example,

the following is an implementation of the profile for an AHU-1 application controller presented a

"C" header file:

```
20 typedef struct snvt_profile
{
    UINT8 direction;    // input, output or input config
    UINT8 snvt_number;  // LCI-defined SNVT number
    char *desc;         // string describing SNVT
25    UINT8 index;      // index of SNVT on controller
} SNVT_PROFILE;
```

\* Automated config =  
pre-load with  
default values.



```

SNVT_PROFILE far __based(__segname("__CODE")) AHU1[44] = {
    {NV_INPUT,S_TEMP_SPACE,"Space Temperature",0},
    {NV_INPUT,S_TEMP_SETP,"Temp Setpoint",1},
    {NV_INPUT,S_OCC_I,"Occupancy Cmd",2},
5   {NV_INPUT,S_LEV_DISC_I,"Reset Runtimes",3},
    {NV_INPUT,S_TIME_I,"System Time",4},
    {NV_INPUT,S_TEMP_OUT,"Outside Temp",5},
    {NV_INPUT,S_LEV_PERCENT,"Outside Humidity",6},
    {NV_OUTPUT,S_TEMP_P,"Space Temperature",7},
10  {NV_OUTPUT,S_HVAC_STATUS_AHU,"Unit Status",8},
    {NV_OUTPUT,S_TEMP_P,"Effective Setpt",9},
    {NV_OUTPUT,S_TIMER,"Occ. Ext. Time Rem.",10},
    {NV_OUTPUT,S_STATE_INPUT,"Input Status",11},
    {NV_OUTPUT,S_OCC_I,"Occupancy Mode",12},
15  {NV_OUTPUT,S_RUNTIME,"Fan Runtime",13},
    {NV_OUTPUT,S_TEMP_P,"Supply Air Temp Out",14},
    {NV_OUTPUT,S_TEMP_P,"Mixed Air Temp Out",15},
    {NV_OUTPUT,S_LEV_PERCENT,"Return Air Humidity",16},
    {NV_OUTPUT,S_FREE_COOL,"In Enthalpy",17},
20  {NV_OUTPUT,S_FREE_COOL,"Out Enthalpy",18},
    {NV_INPUT_CONFIG,S_TEMP_SETP_I,"Occup. Temp Setpts.",19},
    {NV_INPUT_CONFIG,S_TEMP_LIM,"Space Temp Limit",20},
    {NV_INPUT_CONFIG,S_LEV_PERCENT,"Cool Prop. Gain",21},
    {NV_INPUT_CONFIG,S_LEV_PERCENT,"Cool Integ. Gain",22},
25  {NV_INPUT_CONFIG,S_VOLT_I,"Cool Min Output",23},
    {NV_INPUT_CONFIG,S_VOLT_I,"Cool Max Output",24},
    {NV_INPUT_CONFIG,S_LEV_PERCENT,"Heat Prop. Gain",25},
    {NV_INPUT_CONFIG,S_LEV_PERCENT,"Heat Integ. Gain",26},
    {NV_INPUT_CONFIG,S_VOLT_I,"Heat Min Output",27},
30  {NV_INPUT_CONFIG,S_VOLT_I,"Heat Max Output",28},
    {NV_INPUT_CONFIG,S_ECON,"Economizer Type",29},
    {NV_INPUT_CONFIG,S_TEMP_ECON,"Econ. Setpt.",30},
    {NV_INPUT_CONFIG,S_LEV_PERCENT,"Econ. Prop. Gain",31},
    {NV_INPUT_CONFIG,S_LEV_PERCENT,"Econ. Integ. Gain",32},
35  {NV_INPUT_CONFIG,S_LEV_PERCENT,"Min. Fresh Air",33},
    {NV_INPUT_CONFIG,S_FREE_COOL,"Free Cool Setpt.",34},
    {NV_INPUT_CONFIG,S_VOLT_I,"Econ. Min Output",35},
    {NV_INPUT_CONFIG,S_VOLT_I,"Econ. Max Output",36},
    {NV_INPUT_CONFIG,S_FAN,"Fan Type",37},
40  {NV_INPUT_CONFIG,S_TEMP_ADJ,"Setpoint Adjust",38},
    {NV_INPUT_CONFIG,S_EXTEND_TIME,"Occ. Extend Time",39},
    {NV_INPUT_CONFIG,S_RUNTIME,"Fan Runtime Limit",40},
    {NV_INPUT_CONFIG,S_TIME_I,"Occupied Time",41},
    {NV_INPUT_CONFIG,S_TIME_I,"Unoccupied Time",42},
45  {0,0xff,"",0xff},
};// 50

```

As noted above, the local control interface 12 is also preprogrammed with the format of the various explicit message that may be sent or received by the local control interface. This includes the data structures for the various ping messages to be sent to the application controllers, as well as the ping response messages received from the application controllers.

5 Similarly, each application controllers is preprogrammed with the format of the various explicit messages that may be sent or received by that application controller.

B. Self Configuration

As noted previously, the control system 10 provides self-configuration of the various application controllers 14, 15, 16 and 18. In summary, self-configuration is achieved through a series of communications between the local control interface 12 and the newly installed application controller. The self-configuration process 200 will be described in more detail with reference to the flow chart of Figs. 14A-14B. The communications exchange is initiated by activation 202 of the service control button on the application controller. This causes the application controller to send 204 a LonWorks "Service Pin" message that contains the controller's unique Neuron ID. The local control interface 12 maintains a table in nonvolatile memory that has a listing for each application controller known to the local control interface. When the local control interface 12 receives the service pin message, it determines 208 whether it currently has a listing for the application controller's Neuron ID. If it does not, it creates 210 a listing corresponding to that Neuron ID. The local control interface 12 assigns 212 the next available Device ID number to the new application controller and sends 214 a "Device Designation" message to the application controller. This message contains the Device ID for the application controller. The application controller stores the Device ID 216 in nonvolatile memory for later use in sending messages to the local control interface. The local control

interface uses the Device ID from application controller explicit messages to determine which specific controller sent the message. The local control interface then sends 218 a "Controller Interface Identification" message to the application controller, which contains the Neuron ID of the local control interface. The application controller stores 220 the local control interface Neuron ID in nonvolatile memory for later use in sending messages to the local control interface.

The local control interface 12 next places 222 the application controller into a common LonWorks Domain and Subnet and assigns a unique LonWorks Node ID. The local control interface 12 sends 224 an "Update Domain" message to the application controller including the common LonWorks Domain and Subnet and the unique LonWorks Node ID, which are stored 226 in the application controller. The Node ID matches the Device ID assigned earlier. This step is necessary to circumvent several inherent problems with LonWorks networking. First, since the local control interface uses LonWorks request/response messages for the "Network Variable Fetch" and "Network Variable Update" operations, all nodes must have a unique subnet/node combination. Responses are always sent using subnet/node addressing requiring a unique subnet/node for each node. Second, the local control interface preferably uses Echelon's Hosted Node architecture which has the limitation of only being able to receive explicit messages in one Domain, which requires each node to be in the same Domain.

The local control interface 10 preferably includes a plurality of wizards that may be run to specify or adjust the control variables for each of the application controller types.

These wizards facilitate modification and control of the application controllers by providing a simple menu driven GUI that allows viewing and modification of all appropriate control variables.

### C. Controller Supervision

The local control interface 12 monitors the status of and transfers control variable values between application controllers using a periodic message/response methodology. In the preferred embodiment, the local control interface 12 periodically (e.g. once a second) sends a “ping” message to each application controller. If the application controller fails to send an appropriate response to a specified number of successive pings (e.g. three), it is considered to be in a failure state and appropriate action can be taken, for example, setting an alarm or generating a log. This process is also used to exchange information between the local control interface and the application controller using control variables embedded in the ping message and in the responses to ping messages. The data structure of each ping message is preferably preprogrammed into the local control interface 12. The ping message are preferably tailored to correspond with the type of application controller to which it is sent. Alternatively, a single ping message universal to all controller types can be used. With this alternative, each application controller may simply ignore the control variables that are not relevant to its operation.

For example, in the described embodiment, the HVAC control ping is periodically sent by the local control interface 12 to each HVAC application controller (e.g. each DXU-1, DXU-2, AHU-1, FCU-1, FCU-2, FCU-3, FCU-4 and HPU-1). The HVAC control ping preferably includes the system time and the occupancy mode for that specific controller. These control variables are sent to each HVAC application controller in an explicit message using SNVTs. A representation of the HVAC control ping is illustrated in Fig. 8. The HVAC controller’s response demonstrates that it is still communicating with the network and can be used to return control variables to the local control interface in an explicit message using SNVTs. The HVAC controller’s response preferably includes its Device ID, the outside temperature, the

outside humidity and the supply water temperature. A representation of the HVAC response is illustrated in Fig. 9. The information received in response from the HVAC controller can be used by the local control interface and/or propagated to other application controllers by the local control interface.

5                   With some application controllers, the ping response is nothing more than an acknowledgement which indicates to the local control interface 12 that the application controller is on line and has received the ping. For example, the access control ping message is periodically sent to each ACU. The access control ping preferably includes entry side mode, exit side mode, enable/disable flag for entry side, enable/disable flag for exit side, system date, system time, system day of week and ACU Device ID. The entry side mode and exit side mode fields indicate the access mode of the ACU. Typically, the ACU will be capable of operating in four different modes: 1) "card" mode, which requires only card validation to obtain access, 2) "card/pin" mode, which requires card validation and entry of a valid PIN to obtain access, 3) "cipher" mode, which requires entry of a valid four-digit code to gain access and 4) "PIN" mode, which requires entry of a valid PIN to gain access. A representation of the ACU control ping is illustrated in Fig. 10. The ACU response simply includes the IAC Device ID. A representation of the ACU response is illustrated in Fig. 11.

10  
15  
20                   As a further example, a representation of the ASM control ping is illustrated in Fig. 12 and a representation of the ASM response to an ASM ping message is illustrated in Fig. 13. As shown, the response returns the outdoor temperature, outdoor humidity and supply water temperature control variables to the local control interface 12. As with all other messages, the control variables are presented as SNVTs.

As an additional example, a representation of the LCU control ping is illustrated in Fig. 19 and a representation of the LCU response to an LCU control ping is illustrated in Fig. 20. The LCU control ping is intended solely to solicit a response from the LCU, thereby acknowledging its continued connection to the network. As shown, the control ping includes a message number indicating that the message is a control ping. The LCU response message returns only the unit number to the local control interface.

#### D. System-wide Distribution of Process Points

The local control interface 12 also has the ability to distribute various process point (or control variable) data to the application controllers. The process point data can be obtained from sensors, such as those connected to the ASM-1 module. In the preferred embodiment, the local control interface 12 receives the process point data from the ASM-1 module, or other sensor, in response to the ping message sent by the local control interface 12. The local control interface 12 then transmits the process point data to the appropriate application controllers via a network variable write using explicit addressing. The local control interface 12 determines the application controllers that need the information by reviewing the controller profiles provided in the profile database. Alternatively, the process point data can be presented to the appropriate application controllers by including it in the ping message sent to that application controller.

#### E. Access Control

The local control interface 12 oversees access at the various ACUs within the control system 10. In operation, the ACUs send an access request to the local control interface 12 when a valid card reader or keypad entry is obtained from one of the ACU readers/keypads. A representation of the data structure of an access request message is shown in Fig. 15. The

access request is processed by the local control interface and a response is sent to the ACU indicating whether or not access is granted. A representation of the data structure of an access response message is shown in Fig. 16. The local control interface 12 also considers any affect access may have on related occupancy groups, for example, changing an "unoccupied" status to "occupied." If appropriate, the local control interface 12 sends explicit messages to update the status of the appropriate occupancy group. This update will typically occur in the next ping message sent to each application controller with the occupancy group. Once a door is used, the ACU sends a door used message to the local control interface 12. This permits the local control interface 12 to maintain a log of activity and a count of the number of persons in the zone. A representation of the data structure of a door used message is shown in Fig. 17.

The control system 10 is preferably capable of operating in five different access modes: 1) "card" mode, which requires reading of a valid card to obtain access, 2) "card/pin" mode, which requires reading of a valid card and entry of a valid PIN to obtain access, 3) "cipher" mode, which requires entry of a valid four-digit code to gain access, 4) "PIN" mode, which requires entry of a valid PIN to gain access and 5) "free" mode, which permits free access. When an access request is received, it is processed in accordance with the current access mode for that ACU.

The local control interface 12 includes a database supporting up to 500 access cards. Each database entry preferably includes a card number (32-bit raw card number), a card name (18 character ASCII description), a PIN (4-digit BCD number used when card+PIN access is desired), a time/date field (containing the time and date on which the card was last used), a last door field (containing the last door at which the card was used) and an access group field (described below). Cards are added to the database in a general conventional manner, for

example, by presenting them at an ACU or via download from a PC or other similar device. The local control interface 12 is also capable of storing up to four distinct cipher codes.

The local control interface permits cards to be placed into access groups. Access groups specify which doors a card may access and what time periods the card allowed access.

- 5 The local control interface preferably supports at least 16 access groups.

The local control interface also permits ACUs to control occupancy for occupancy groups, if desired. To provide ACU occupancy control, the local control interface maintains a person count by tracking the number of entries and exits into an area. If the person count is not zero, the local control interface sets the status of the occupancy group to "occupied."

10 Although access is preferably governed by the local control interface, each ACU application controller preferably includes a local "per-door" database for validating access in the event of loss of communications with the local control interface. When the ACU send an access request to the local control interface 12 that is not answered within 1/2 second, the ACU will attempt to validate the access using the local database. When the ACU validates an access request locally, it will also preferably generate a time-stamped transaction log indicating the result of the access attempt.

15 In a preferred embodiment, the ACUs also detects certain alarm conditions and sends appropriate messages to the local control interface 12 when an alarm event occurs. Preferably, the ACU monitors the status of the supervised inputs to determine when a "door  
20 propped," "door forced," or "input tampering" condition occurs. A door propped alarm is generated when an individual, who has gained access, leaves the door open for longer than a predefined access time. A door forced alarm is generated when the door is opened without



proper access authorization. A representation of the data structure of an access alarm is shown in Fig. 18.

#### F. Lighting Control

The local control interface 12 also manages operation of lighting applications within the building via one or more LCUs. As noted above, the LCUs are designed to control commercial lighting circuits, which may include interior lighting, parking lot lights and signage. In the described embodiment, each LCU controls the state of eight individual lighting circuits. The LCUs provides for eight lighting zones that permit group control of the lighting applications. More specifically, each circuit on each LCU can be associated with one or more of the eight lighting zones. The status of each circuit is affected by controlling the occupancy status of the corresponding lighting zone. The lighting zone associations for each LCU are configured via the local control interface 12. Each LCU maintains a database of the lighting zone associations for each of its circuits. The LCU controls the on/off state of each circuit based on the occupancy status of the zone associated with that circuit. The lighting zones can, in turn, be associated with occupancy groups, thereby permitting the occupancy of lighting zones to be collectively controlled with other applications within a given occupancy group.

The local control interface 12 includes means for transmitting control messages to the LCU to advise the LCU of the occupancy status of the lighting zones. This permits the local control interface 12 to control the occupancy status of the lighting zones in accordance with occupancy group schedules maintained on the local control interface 12, as well as in accordance with other occupancy status changes, such as may be triggered by an access event. In operation, a change in occupancy status for a given zone, whether resulting from a schedule event or from another occupancy effecting event, is transmitted by the local control interface 12 to each LCU.

Eight different command messages are used to discern between the eight lighting zones. For example, a first command message is used to communicate the occupancy status of zone 1 and a second command message is used to communicate the occupancy status of zone 2. Upon receipt of the command message, each LCU reviews its database of lighting zone associations to determine if the command message is relevant to any of its circuits. If so, the LCU sets the on/off status of the appropriate circuit(s) in accordance with the occupancy status contained in the command message. Each LCU may also maintain a local back-up copy of the schedule to permit continued operation in the event of a local control interface or network failure.

Each LCU also includes eight inputs used primarily for override switches. Each override switch can be associated with one or more lighting zones so that actuation of the switch affects the occupancy status of these lighting zones. As with the circuits, the lighting zone associations of the inputs are preferably set via the local control interface 12, with each LCU maintaining a local database of the associations for each of its inputs. In operation, actuation of an override switch cause the associated LCU to determine the lighting zones to which the switch is a member and affect the on/off status of all circuits on the LCU associated with that lighting zone. The LCU also sends a peer-to-peer message to all other LCUs on the network indicating the change in the occupancy status of the particular lighting zone. Each of these other LCUs then affects the on/off status of all circuits on that LCU that are associated with the specified lighting zone. This permits integration of override events between LCUs without intervention from the local control interface.

#### G. Alarms

Various application controllers have the ability to send text-based alarms to the local control interface 12 to indicate extraordinary conditions, for example, several ACU alarms

were described in the immediately preceding section on Access Control. The local control interface 12 has the ability to display and store these alarms. Preferably, each alarm includes a unit name, time/date of occurrence and up to 40 characters of text. The text field can be used to provide meaningful text based descriptions of the alarm event. A representation of the data structure of an alarm is shown in Fig. 18. Although the alarms are preferably responded to manually, the local control interface 12 can be configured to provide an automated response when desirable, for example, the local control interface 12 can be programmed to repeatedly flash the lights in a zone in the event of a "door forced" alarm.

#### H. Control Software

As described above, the local control interface and the application controllers operate in accordance with installed control software. Typically, appropriate control software is preloaded into the local control interface and the application controllers. In some applications, this may not be desirable or possible. Accordingly, the local control interface 12 preferably includes means for storing a database of application controller software images and means for downloading the application controller software images into the application controllers. Generally, the application controller software images will be downloaded into the application controller during the self-configuration process to provide the application controller with the applicable control software. The local control interface 12 can, however, be used to download control software to the application controller even after self-configuration. This capability can be used to provide the initial installation of control software on an application controller or to update/upgrade the existing control software on an application controller. Similarly, the local control interface preferably includes means for downloading the control software of the local control interface and means for installing the control software on the local control interface. This

functionality is particularly useful in permitting customization and update/upgrade of the control software for the local control software.

In control systems where control software is to be downloaded, the local control interface and/or the application controllers can be preprogrammed with only minimal basic networking and configuration functionality. This minimal programming permits the local control interface and/or application controllers to be installed on the network and provides for the downloading and installation of the control software.

The local control interface 12 preferably includes means to permit the remote downloading of control software, including application controller software images and local control interface software images. This enables the local control interface and the application controllers to be updated/upgraded via a remote Internet, dialed or direct connection.

A flexible alternative to conventional control software is to preprogram the local control interface and/or application controllers with a generic programming language that permits operation of the device in accordance with custom control programs downloaded after self-configuration. The generic programming language provides an engine capable of controlling operation of a device in accordance with instructions contained in the custom control program. In this alternative, the local control interface includes means for downloading custom control programs from a remote Internet, dialed or direct connection and/or for creating custom control programs, as well as means for downloading the custom control programs to the appropriate application controllers.

The above description is that of a preferred embodiment of the invention. Various alterations and changes can be made without departing from the spirit and broader aspects of the invention as defined in the appended claims, which are to be interpreted in accordance with the

principles of patent law including the doctrine of equivalents. Any reference to claim elements in the singular, for example, using the articles a, an, the or said, is not to be construed as limiting the element to the singular.

20170904036